



S735



7165-0328:0204

NYC Fire Dept.  
Certificate of  
Approval  
6184

Approved for DACT or Stand  
Alone IP Communications

**Features:**

- 6 Programmable Initiating Device Circuits
- Class A or Class B Waterflow Initiating Circuit
- 2 Wire Smoke Detector Compatibility
- 1.0 Amp Power Supply
- 1 Notification Circuit rated at 0.5 Amps Regulated
- Strobe Synchronization for Potter/AMSECO, Gentex, System Sensor and Cooper/Wheelock
- 0.5 Amp Auxiliary Power, Programmable as Constant or Resettable
- 2 x 16 LCD display with system LEDs for clear system status
- Keypad for system features
- P-Link for Remote Annunciator Connections
- Capacity to charge and house 18AH batteries
- Onboard Dual Line Digital Alarm Communicator
- Built-in Ethernet Connection with listed IP Communicator
- Ability to E-mail system status, reports and system configuration
- Service Reminder E-mails

*Electrical Specs*

*AC Mains*

- 1.0 amp @ 120 VAC 60 Hz

*Battery*

- 105 mA Standby
- 160 mA Alarm

*Dimensions*

- 18 1/2" H x 14 1/4 W x 4 3/4" D

**General Description**

The PFC-6006 is a listed small conventional fire system ideally suited to monitor a small fire system such as a fire sprinkler system. The first input is selectable as a Class A or Class B water flow input and the other five zones are selectable from a menu of options including two-wire smoke detection. The panel has a 1.0 amp power supply that powers the panel, charges the batteries and supplies 0.5 amps to a notification appliance circuit and 0.5 amps of auxiliary power. The auxiliary power is programmable as constant or resettable.

The control panel is in a metal cabinet with a key lock and lexan window for viewing the system status. The printed circuit assembly is mounted for quick removal and installation to allow the cabinet to be installed with minimal effort. The cabinet houses up to two 12VDC, 18 AH batteries.

The display is a thirty-two (32) character LCD with system status LEDs. The system status is clearly displayed and the panel includes a history buffer for past events. The key pad allows navigation into the system menu, limited programming and system control. The condition and events on the panel are clearly displayed to allow the user and installer to determine the system status.

The panel has a dual telephone line digital alarm communicator transmitter (DACT) built on-board. One or both telephone lines may be enabled to allow communication to a remote monitoring station. In addition, an updated panel configuration may be sent to the panel through the telephone lines. The panel has line in and line out to allow the panel to be installed ahead of other telephone equipment on the premises.

The panel will support up to four (4) of the RA-6075 remote annunciators on the P-Link bus. These annunciators include a metal enclosure with a key lock and provide full functionality of the system.

The panel is pre-programmed from the factory for monitoring a typical wet or dry fire sprinkler system. The programming may be changed using the Potter Fire Panel Programmer (available free from [www.pottersignal.com](http://www.pottersignal.com)) and a standard Ethernet cable. The default program is as follows:

- Input 1 - Waterflow
- Input 2 - Smoke Detection (two-wire)
- Input 3 - Manual Pull Station
- Input 4 - Non-Latching Supervisory
- Input 5 - Valve Tamper
- Input 6 - Valve Tamper

### General Description (Cont.)

In the standard program, Input 1 is defaulted as a Water flow zone. Input 1 is the only Class A/Class B zone. The panel will automatically determine Class A or B based on wiring and the presence of the end of line resistor. All of the inputs may be programmed for General Alarm, Waterflow, Two-Wire Smoke Detector, Heat Detector, Manual Pull Station, Non-latching Supervisory, Latching Supervisory, or Valve Tamper.

The NAC is listed for strobe synchronization and the panel is listed with Potter/AMSECO, Gentex, System Sensor, and Cooper Wheelock signals. Please refer to the Potter Notification Compatibility Document for the maximum number of strobe devices that may be connected. The maximum output is 0.5 amps.

The Ethernet connection may be connected to a building network with Internet to provide e-mail notifications of system status, reports, or system configuration. In addition, the Ethernet connection is listed for IP reporting to a monitoring station.

