



### **Features**

- · Provides Class A connection for SLC, NACs, & PLink
- · Monts to framework inside panel enclosure
- Allows for independent circuit selection of Class A operation
- Product includes 5 year warranty
- UUKL Listed for Smoke Control





## Description

The CA-6075 is a Class A Expander. The CA-6075 allows for Class A wiring of the built in SLC circuit, P-Link communication bus and two (2) built in NAC circuits. The CA-6075 mounts to the provided framework in the fire alarm control panel. The Class A operation can be independently selected for the P-Link and SLC circuits using the Potter Fire Panel Programmer Software

## Installation

Connection of the CA-6075 Class A Expander to the addressable control panel:

1. Remove two (2) #6-32x7/8 screws (item #1 shown below) from the control panel and retain for use in step #3.

2. Install 5050793 Bracket, inserting end tabs into slots on the control panel User Interface bracket.

3. Secure 5050793 bracket to the control panel using the two (2) screws (item #1) that were removed in step #1.

4. Slide the CA-6075 Class A Expander over the two (2) guide pins on the 5050793 bracket. Seat the CA-6075 on the 5050793 bracket so the connector on the back of the CA-6075 is fully engaged with the connector on the control panel.

5. Secure the CA-6075 to the 5050793 bracket using two (2) #6-32x1/4 screws provided (shown on page 2).

## **Technical Specifications**

| Standby Current                  | 12 mA   |
|----------------------------------|---|
| Alarm Current                    | 44 mA   |
| Ambient Operating<br>Temperature | 32°F - 120°F (0°C - 49°C) 10%-93% @<br>30°C (86°F) non-condensing humidity  |
| Maximum CA-6075<br>Expanders     | 1   |
| Compatible Panels                | IPA-60, IPA-100<br>AFC-50, AFC-100, ARC-100<br>PFC-6030*, PFC-6075*, PFC-6200*<br>PFC-6075R*, P100*, P200*, P300* |

#### \*Legacy Product

#### Note:

Not for use with IPA-4000, AFC-1000, PFC-6800 and P400(R) control panels.

## NOTICE

Install in accordance with compatible Fire Alarm Control Panel installation manual.


Potter Electric Signal Company, LLC

St. Louis, MO • P






# **CA-6075 Class A Installation Diagram** *Fig 1*



## **Installed Class A Card**



## **Ordering Information**

| Model   | Description      | Stock No. |
|---------|------------------|-----------|
| CA-6075 | Class A Expander | 3006459   |

Potter Electric Signal Company, LLC • St. Louis, MO • Phone: 800-325-3936 • www.pottersignal.com